

<u>PTO Code</u> 356AE 	<u>Pump Side Connection Type of PTO</u> 6 Keyway Milling Spindle Output 6x21x25 - UNI 	<u>Main Transmission Model</u> ALVANT AUMARK C FOTON BJ 1061 OTOKAR ATLAS W1 LYYS 1B WAN LI YANG WANIER 6 S 51 B WLY 6 S 51 B - 40 A - 00	Gear Type : Left Helix PTO Type : Double Thread Torque Nm : 200 Power Kw : 20 Output Ratio 1000 Rpm : 1:1,08 Mounting Location : Left Side Control System : Pneumatic PTO Shaft Rotation : Rihgt — (Pump Shaft Rotation : Left) Weight Kg. : 13	
<u>PTO Code</u> 008AE 	<u>Pump Side Connection Type of PTO</u> 6 Keyway Milling Spindle Output 6x21x25 - UNI 	<u>Main Transmission Model</u> FOTON BJ 1061 OTOKAR ATLAS WANIER 6 S 51 B WLY 6 S 51 B - 40 B WLY6S51 B	Gear Type : Left Helix PTO Type : Double Thread Torque Nm : 200 Power Kw : 20 Output Ratio 1000 Rpm : 1:1,13 Mounting Location : Left Side Control System : Pneumatic PTO Shaft Rotation : Rihgt — (Pump Shaft Rotation : Left) Weight Kg. : 12,60	
<u>PTO Code</u> 323AE 	<u>Pump Side Connection Type of PTO</u> 6 Keyway Milling Spindle Output 6x21x25 - UNI 	<u>Main Transmission Model</u> HINO LJ 06 S WLY 6 S 51 B - 33 - 00	Gear Type : Left Helix PTO Type : Double Thread Torque Nm : 340 Power Kw : 35 Output Ratio 1000 Rpm : 1:1,19 Mounting Location : Left Side Control System : Pneumatic PTO Shaft Rotation : Rihgt — (Pump Shaft Rotation : Left) Weight Kg. : 12,50	